
TELECRANE F21-4S

Specifications

The TELECRANE model F21-4S Industrial Radio Remote Control system is rugged and reliable, suitable for use with 2-motion, 1-speed monorails (up/down/east/west motions), A/B/Both hoist installations, doors, motors, and many other industrial applications. The receiver mounts with a single vibration-damping threaded stud and is pre-cabled for easy installation, and the transmitter is lightweight and convenient to use. The TELECRANE model F21-4S is the safe solution to your wireless control needs.



4
1
110V AC standard; 220V AC available
1
2-motion, 1-speed monorail hoist
250 ft.
310-320 MHz
Crystal
128-bit framing protocol with 32-bit serial number embedded; error detection and correction encoded
IP65
FCC Part 15 accepted- No license needed
1 year against defects in manufacture (casing and consumable parts excepted)
-35 to 75 deg C (-31 to 167 deg F)
30% glass-fiber reinforced nylon-6
7.4 in. (not including cable) x 3.4 in. x 7.1 in. (including antenna)
F21-4S-RX

RX power supply input	110V AC standard; 220V AC available
RX relay rating	10A at 250V AC
RX weight	2 lbs.
TX part number	F21-4S-TX
TX size	6.2 in. x 2.4 in. x 2 in.
TX weight	9 oz.
TX power source	2 AA alkaline batteries
TX battery power indication	LED
TX button specifications	Tested to 2,000,000 operations
TX start key	3-position, removable OFF/ON/START rotary key
TX stop button	Push-to-activate, twist-to-release emergency stop button
Transmitter Specifications	
Operating distance	250 ft.
Frequency band	310-320 MHz
Frequency generation	Crystal
Security coding	128-bit framing protocol with 32-bit serial number embedded; error detection and correction encoded
Environmental rating	IP65
Licensing	FCC Part 15 accepted- No license needed
Warranty	1 year against defects in manufacture (casing and consumable parts excepted)
Temperature rating	-35 to 75 deg C (-31 to 167 deg F)
Case material	30% glass-fiber reinforced nylon-6
RX part number	F21-4S-RX
TX size	6.2 in. x 2.4 in. x 2 in.

TX power source	2 AA alkaline batteries
TX battery power indication	LED
TX button specifications	Tested to 2,000,000 operations
TX start key	3-position, removable OFF/ON/START rotary key
TX stop button	Push-to-activate, twist-to-release emergency stop button
Receiver Specifications	
Typical applications	2-motion, 1-speed monorail hoist
Operating distance	250 ft.
Frequency band	310-320 MHz
Frequency generation	Crystal
Environmental rating	IP65
Licensing	FCC Part 15 accepted- No license needed
Warranty	1 year against defects in manufacture (casing and consumable parts excepted)
Temperature rating	-35 to 75 deg C (-31 to 167 deg F)
Case material	30% glass-fiber reinforced nylon-6
RX size	7.4 in. (not including cable) x 3.4 in. x 7.1 in. (including antenna)
RX power supply input	110V AC standard; 220V AC available
RX relay rating	10A at 250V AC
RX weight	2 lbs.

